

## Z-Wave Protocol Implementation Conformance Statement

### UPowerSwitch

#### General Information

<b>Product Identifier:</b>	UPowerSwitch
<b>Brand Name:</b>	LG U+
<b>Product Version:</b>	HW: 1 FW: 10.11
<b>Z-Wave Certification #:</b>	ZC12-19100017

#### Product Features

<b>Color</b>	White
<b>Electric Load Type</b>	Fluorescent Incandescent LED
<b>Firmware Updatable</b>	Updatable by Manufacturer Representative
<b>Outdoor Use</b>	No
<b>Switch Load Capacity Current</b>	3A
<b>Switch Load Capacity Volt-Ampere</b>	AC220V
<b>Switch Load Capacity Watts</b>	600W
<b>Switch Type</b>	Push Button with Indicator

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

**UPowerSwitch**

## Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	South Korea
<b>Z-Wave Product ID:</b>	0x0002
<b>Z-Wave Product Type:</b>	0x0057
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.11.0
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch / Listening Sleeping Slave

## Association Group Information

<b>Group # / Max</b>	<b>Description</b>
----------------------	--------------------

### Nodes

1 / 3	Z-Wave Plus Lifeline
-------	----------------------

### Supported Command Classes (21):

Association Group Information V3	Association V2
Basic V2	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V3
Multi-Channel V4	Notification V8
Powerlevel	Security S0
Security S2	Sensor Multilevel V5
Supervision	Switch Binary V2
Transport Service V2	Version V3
Z-Wave Plus Info V2	