

Z-Wave Protocol Implementation Conformance Statement

B.One Motion Sensor

General Information

Product Identifier:	B1MS02-ZW-IN
Brand Name:	B.One
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-19126820

Product Features

Battery Type	CR123A
Sensors	Air Temperature
Color	White
Supported Notification Types	Home Security
Battery Quantity	1
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	India
Z-Wave Product ID:	0x0102
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

B.One Motion Sensor

Association Group Information

Group # / Max Description

Nodes

- 1 / 5 Z-Wave Plus Lifeline: 1. Notification Report. Sensor will send Notification Report to the associated nodes when Motion Sensor is removed or/and PIR is triggered. 2. Battery Report. Motion Sensor will send Battery Report when the battery level is low and the battery report's value is 0xFF. 3. Device Reset Locally Notification.
- 2 / 5 1. Basic Set. Motion Sensor will send Basic Set to associated nodes when the PIR is triggered.

Supported Command Classes (18):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific	Manufacturer Specific V2
Notification V3	Notification V5
Powerlevel	Security S0
Security S2	Supervision
Transport Service V2	Version V2
Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic