

## Z-Wave Protocol Implementation Conformance Statement

### Z-Wave Mutil-relay

#### General Information

<b>Product Identifier:</b>	ZW11
<b>Brand Name:</b>	Zooz
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-19126825

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Color</b>	Black

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xa00a
<b>Z-Wave Product Type:</b>	0xa000
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.82.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 1	Z-Wave plug lifeline
2 / 5	basic set command

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Mutil-relay

4 / 5                  basic set command

### Supported Command Classes (16):

Association Group Info	Association V2
Basic V2	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Multi-Channel V4	Powerlevel
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic V2