

## Z-Wave Protocol Implementation Conformance Statement

### Double-Switch

#### General Information

<b>Product Identifier:</b>	0x00/9498
<b>Brand Name:</b>	TechniSat
<b>Product Version:</b>	HW: 6 FW: 2.00
<b>Z-Wave Certification #:</b>	ZC10-20036884

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Neutral Wire Required</b>	Yes

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1A91
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.82.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 1	The lifeline group reports the device's status.
2 / 10	Sends basic set commands according to the current state of switch 1 of the device to associated devices.

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Double-Switch

3 / 10      Sends basic set commands according to the current state of switch 2 of the device to associated devices.

### Supported Command Classes (20):

- |                              |                              |
|------------------------------|------------------------------|
| Association Group Info       | Association V2               |
| Basic V2                     | Central Scene V3             |
| Configuration                | Device Reset Locally         |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2     |
| Meter V4                     | Multi-Channel Association V3 |
| Multi-Channel V4             | Notification V8              |
| Powerlevel                   | Security S0                  |
| Security S2                  | Supervision                  |
| Switch Binary                | Transport Service V2         |
| Version V3                   | Z-Wave Plus Info V2          |

### Controlled Command Classes (1):

- Basic V2