

Z-Wave Protocol Implementation Conformance Statement

LED Dimmer Z-Wave 200W

General Information

| | |
|--------------------------------|----------------|
| Product Identifier: | 1402756 |
| Brand Name: | Namron |
| Product Version: | HW: 1 FW: 1.17 |
| Z-Wave Certification #: | ZC10-20036893 |

Product Features

| | |
|---|----|
| Controller Supports Multiple Networks | No |
| Controller Supports Multiple Z-Wave Interfaces | No |

Z-Wave Product Information

| | |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|---------------------------------------|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x0001 |
| Z-Wave Product Type: | 0x0202 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.81.03 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Light Dimmer Switch / Always On Slave |

Association Group Information

| Group # / Max | Description |
|---------------|---|
| Nodes | |
| 1 / 5 | The ASSIC or Lifeline:4C 69 65 6C 69 6E 65 1.when press and hold down Reset button over 5s to reset the dimmer send"Device Reset locally Notification CC" to associated devices of this group to report factory reset |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

LED Dimmer Z-Wave 200W

Supported Command Classes (15):

Association Group Info
Basic
Device Reset Locally
Manufacturer Specific V2
Security S0
Supervision
Transport Service V2
Z-Wave Plus Info V2

Association V2
Configuration
Firmware Update Meta-Data V4
Powerlevel
Security S2
Switch Multilevel V2
Version V2