

Z-Wave Protocol Implementation Conformance Statement

Era Inn Edge S AC ZW BD

General Information

Product Identifier:	E EDGE SI 620 AC ZWA BD
Brand Name:	FIBARO
Product Version:	HW: 186 FW: 1.02:01.00
Z-Wave Certification #:	ZC10-20056911

Product Features

Z-Wave Scene Type	Scene
Firmware Updatable	Updatable by Consumer by RF
Window Covering Control Features	Manual Calibration Position Aware Supports Up/Down Motion

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x00BA
Z-Wave Product Type:	0x0103
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.81.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Window Covering - Pos/End Aware / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Era Inn Edge S AC ZW BD

- 2 / 5 Retransmit a Basic Set, Multilevel Switch Set, Multilevel Switch Start Level Change, Multilevel Switch Stop Level Change or Scene Activate Set to the nodes associated.
- 3 / 5 If node receives Configuration Bulk Set or Configuration Set (parameter MUST be in the range from 39 to 43), it will send Configuration Bulk Set with Handshake=0 or Configuration Set to nodes associated.

Supported Command Classes (19):

Application Status	Association Group Info
Association V2	Basic V2
Configuration V2	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Notification V8	Powerlevel
Scene Activation	Scene Actuator Conf
Security S0	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (4):

Basic V2	Configuration V2
Scene Activation	Switch Multilevel V4