

## Z-Wave Protocol Implementation Conformance Statement

### 2 Wire Dimmer

#### General Information

<b>Product Identifier:</b>	PAD15
<b>Brand Name:</b>	Philio
<b>Product Version:</b>	HW: 1 FW: 1.01
<b>Z-Wave Certification #:</b>	ZC12-20070082

#### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Don't know
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x007e
<b>Z-Wave Product Type:</b>	0x0005
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Multilevel Switch / Always On Slave

#### Association Group Information

<b>Group # / Max Nodes</b>	<b>Description</b>
1 / 5	1. Grouping 1 Lifeline (Maximum 5 nodes). 2. MULTILEVEL_SWITCH_REPORT When "on" or "off" state has been changed, it will send Multilevel Switch Report to the nodes of Grouping 1. 3. NOTIFICATION_REPORT When overload occurred. 4. DEVICE_RESET_LOCALLY_NOTIFICATION When PAD15 is reset manually, it

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 2 Wire Dimmer

### Supported Command Classes (18):

Association Group Information V3

Basic V2

Device Reset Locally

Indicator V3

Multi-Channel Association V3

Powerlevel

Security S2

Switch Multilevel V4

Version V3

Association V2

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific V2

Notification V8

Security S0

Supervision

Transport Service V2

Z-Wave Plus Info V2