

## Z-Wave Protocol Implementation Conformance Statement

### ClareOne Siren

#### General Information

<b>Product Identifier:</b>	ZW080-A17
<b>Brand Name:</b>	Clare Controls
<b>Product Version:</b>	HW: 80 FW: 11.00
<b>Z-Wave Certification #:</b>	ZC10-20086964

#### Product Features

<b>Z-Wave Scene Type</b>	Scene
<b>Firmware Updatable</b>	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0050
<b>Z-Wave Product Type:</b>	0x0103
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.82.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Sound Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 5	Lifeline group. Device Reset Locally Notification: Issued when Factory Reset is performed. Sound Switch Tone Play Report: Issued when a tone has started playing. Sound Switch Configuration Report: Issued when

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

ClareOne Siren

2 / 5                      Retransmit a Basic Set, Switch Binary Set, Sound Switch Tone Play Set to the nodes associated.

## Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S0	Security S2
Sound Switch	Supervision
Switch Binary	Transport Service V2
Version V2	Z-Wave Plus Info V2