

## Z-Wave Protocol Implementation Conformance Statement

# Portable Remote, Simple Controller, 2 Button

### General Information

<b>Product Identifier:</b>	53829/ZW5313
<b>Brand Name:</b>	Jasco
<b>Product Version:</b>	HW: 1 FW: 7.04
<b>Z-Wave Certification #:</b>	ZC12-20090119

### Product Features

<b>Battery Type</b>	CR2032
<b>Battery Quantity</b>	2
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Z-Wave Scene Type</b>	Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3136
<b>Z-Wave Product Type:</b>	0x4843
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Central Scene Device / Reporting Sleeping Slave

### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Portable Remote, Simple Controller, 2 Button

- 2 / 5 Association Group 2 supports Basic Set and is controlled by pressing the UP or Down button once.
- 3 / 5 Association Group 3 supports Basic Set and is controlled by double pressing the UP or Down button twice.

### Supported Command Classes (19):

Application Status	Association Group Information V3
Association V2	Battery
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V5
Indicator V3	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	