

## Z-Wave Protocol Implementation Conformance Statement

# In-Wall Tamper Resistant Smart Outlet

### General Information

<b>Product Identifier:</b>	55257/ZW1002
<b>Brand Name:</b>	Jasco
<b>Product Version:</b>	HW: 255 FW: 5.51
<b>Z-Wave Certification #:</b>	ZC10-20086966

### Product Features

<b>Neutral Wire Required</b>	Yes
<b>Switch Load Capacity Current</b>	15
<b>Switch Load Capacity Watts</b>	1800
<b>Switch Type</b>	Push Button with Indicator
<b>Z-Wave Scene Type</b>	Central Scene
<b>Electric Load Type</b>	(No feature option values set for this feature)
<b>Firmware Updatable</b>	Updatable by Consumer by RF

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-Wall Tamper Resistant Smart Outlet

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3235
<b>Z-Wave Product Type:</b>	0x4952
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.82.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max**    **Description**

#### Nodes

1 / 5	Z-Wave Plus Lifeline
2 / 5	Supports Basic Set and is controlled with the local load
3 / 5	Supports Basic Set and is controlled by pressing the On or Off button

#### Supported Command Classes (18):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S2	Supervision
Switch Binary V2	Transport Service V2
Version V3	Z-Wave Plus Info V2

#### Controlled Command Classes (1):

Basic V2