

## Z-Wave Protocol Implementation Conformance Statement

### Floodlight Sensor

#### General Information

<b>Product Identifier:</b>	HS-FLS100-G2
<b>Brand Name:</b>	HomeSeer
<b>Product Version:</b>	HW: 1 FW: 1.00:00.07
<b>Z-Wave Certification #:</b>	ZC10-20096976

#### Product Features

<b>Switch Load Capacity Watts</b>	300
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Outdoor Use</b>	Yes

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x000C
<b>Z-Wave Product Type:</b>	0x0201
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.82.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Always On Slave

#### Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Floodlight Sensor

2 / 4 Control of other Z-Wave devices via PIR sensor

### Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S2	Sensor Binary
Sensor Multilevel V5	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2