

Z-Wave Protocol Implementation Conformance Statement

Scene Controller

General Information

Product Identifier:	ZA-207001
Brand Name:	Ness
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-20106991

Product Features

Battery Type	LIR2450
Battery Quantity	1
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x000B
Z-Wave Product Type:	0x0202
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.08
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Wall Controller / Portable Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Scene Controller

- 2 / 5 allows Scene Controller sends basic set command when the button 1 is triggered
- 3 / 5 allows Scene Controller sends switch multilevel set, multilevel start level change and multilevel stop level change command when the button 1 is triggered.
- 4 / 5 allows Scene Controller sends basic set command when the button 2 is triggered.
- 5 / 5 allows Scene Controller sends switch multilevel set, multilevel start level change and multilevel stop level change command when the button 2 is triggered.
- 6 / 5 allows Scene Controller sends basic set command when the button 3 is triggered.
- 7 / 5 allows Scene Controller sends switch multilevel set, multilevel start level change and multilevel stop level change command when the button 3 is triggered.
- 8 / 5 allows Scene Controller sends basic set command when the button 4 is triggered.
- 9 / 5 allows Scene Controller sends switch multilevel set, multilevel start level change and multilevel stop level change command when the button 4 is triggered.

Supported Command Classes (13):

Association Group Info	Association V2
Battery	Central Scene V2
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Powerlevel	Security S0
Version V2	Wake Up V2
Z-Wave Plus Info V2	

Controlled Command Classes (4):

Basic	Battery
Central Scene V2	Switch Multilevel V2