



## Z-Wave Protocol Implementation Conformance Statement

# Enbrighten Z-Wave Plus In-Wall Smart Dimmer, No Neutral, LED-CFL

### General Information

<b>Product Identifier:</b>	52252/52253/ZW3012
<b>Brand Name:</b>	Enbrighten
<b>Product Version:</b>	HW: 1 FW: 7.06
<b>Z-Wave Certification #:</b>	ZC12-20120145

### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Watts</b>	300
<b>Switch Type</b>	Decorator Paddle Push with Indicator
<b>Z-Wave Scene Type</b>	Scene & Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3333
<b>Z-Wave Product Type:</b>	0x4944
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Multilevel Switch / Always On Slave

### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Enbrighten Z-Wave Plus In-Wall Smart Dimmer, No Neutral, LED-CFL, White and Light Almond Paddles

- 2 / 5 Association Group 2 supports Basic Set and is controlled with the local load
- 3 / 5 Association Group 3 supports Basic Set and is controlled by double pressing the ON/OFF button

### Supported Command Classes (18):

Application Status	Association Group Information V3
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V5
Indicator V3	Manufacturer Specific
Multi-Channel Association V3	Powerlevel
Security S2	Supervision
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2