

Z-Wave Protocol Implementation Conformance Statement

Strips Comfort 700

General Information

Product Identifier:	11 02 021
Brand Name:	Sensitive
Product Version:	HW: 1 FW: 2.02
Z-Wave Certification #:	ZC12-21030197

Product Features

Battery Type	Built in 3.0V LiMnO2
Color	White
Firmware Updatable	Updatable by Consumer by RF
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe), South Africa, UAE
Z-Wave Product ID:	0x000C
Z-Wave Product Type:	0x0004
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.13.7
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Strips Comfort 700

- 2 / 5 OFF – 00 (0x00) ON – 255 (0xFF) This association shall work for both Binary Switch and Timed Switch functions set in configuration parameter 29 – Slider switch function
- 3 / 5 OFF – 00 (0x00) ON – 255 (0xFF) Values could be modified using the configuration parameters 33 & 34 This association shall work for both Binary Switch and Timed Switch functions set in configuration parameter 29 – Slider switch function
- 4 / 5 Pre-requisite: configuration parameter no. 29 – Slider switch function set to 1 (Binary Switch) OFF – 00 (0x00) or The value set in the configuration parameter 35, Default is Heat Mode On – 01 (0x01)
- 5 / 5 Temperature Value
- 6 / 5 High temperature alarm = OFF – 00 (0x00) Low temperature alarm = ON – 255 (0xFF) Values could be modified using the configuration parameters 36 & 37
- 7 / 5 High ambient light (LUX) level trigger = ON – 255 (0xFF) Low ambient light (LUX) level trigger = OFF – 00 (0x00) Values could be modified using the configuration parameters 38 & 39

Supported Command Classes (20):

Application Status	Association Group Information V3
Association V2	Battery
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V5
Indicator V3	Manufacturer Specific V2
Multi-Channel Association V3	Notification V8
Powerlevel	Security S2
Sensor Multilevel V11	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2