

## Z-Wave Protocol Implementation Conformance Statement

### In-Wall Smart Switch (120/277VAC)

#### General Information

<b>Product Identifier:</b>	43072/ZW4008DV
<b>Brand Name:</b>	Enbrighten
<b>Product Version:</b>	HW: 255 FW: 5.54
<b>Z-Wave Certification #:</b>	ZC10-21047023

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Neutral Wire Required</b>	Yes
<b>Z-Wave Scene Type</b>	Scene & Central Scene
<b>Switch Load Capacity Watts</b>	1800

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3139
<b>Z-Wave Product Type:</b>	0x4952
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-Wall Smart Switch (120/277VAC)

- 2 / 5 Supports Basic Set and is controlled by pressing the ON or OFF button with the local load.
- 3 / 5 Supports Basic Set and is controlled by double pressing the ON or OFF button.

### Supported Command Classes (18):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S2	Supervision
Switch Binary V2	Transport Service V2
Version V3	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic V2