

## Z-Wave Protocol Implementation Conformance Statement

### On/Off Switch (Red Series)

#### General Information

<b>Product Identifier:</b>	LZW30-SN
<b>Brand Name:</b>	Inovelli
<b>Product Version:</b>	HW: 1 FW: 1.21
<b>Z-Wave Certification #:</b>	ZC10-21067042

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0002
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

##### Group # / Max Description

##### Nodes

1 / 5	Members of this group will receive unsolicited messages related to the status of the switch.
2 / 5	1. Single press up button sends BasicSet (0xFF) and 2. Single press down sends BasicSet (0x00).

##### Supported Command Classes (19):

Application Status	Association Group Info
Association V2	Basic
Central Scene V3	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Meter V3
Powerlevel	Protection V2
Security S0	Security S2

# Z-Wave Protocol Implementation Conformance Statement

**(Continued)**

## On/Off Switch (Red Series)

### Controlled Command Classes (1):

Basic