

## Z-Wave Protocol Implementation Conformance Statement

# S2 Remote Control Switch

### General Information

<b>Product Identifier:</b>	MR40Z
<b>Brand Name:</b>	Minoston
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC12-21070256

### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Watts</b>	1200W
<b>Switch Type</b>	Push Button

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xD001
<b>Z-Wave Product Type:</b>	0x0924
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Central Scene Device / Reporting Sleeping Slave

### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## S2 Remote Control Switch

2 / 5 BASIC SET COMMAND  
3 / 5 SWITCH\_MULTILEVEL\_CHANGE

### Supported Command Classes (17):

Association Group Information V3	Association V3
Battery	Central Scene V3
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V4
Powerlevel	Security S2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	