

## Z-Wave Protocol Implementation Conformance Statement

### In Wall Dual relay switch module

#### General Information

<b>Product Identifier:</b>	PAN30-CN
<b>Brand Name:</b>	Philio
<b>Product Version:</b>	HW: 1 FW: 1.01
<b>Z-Wave Certification #:</b>	ZC12-21070269

#### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Current</b>	6.5 Amps

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	China
<b>Z-Wave Product ID:</b>	0x0077
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.15.1
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch / Always On Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In Wall Dual relay switch module

- 2 / 5 For group 2, the Switch will report ON/OFF status of Relay1.
- 3 / 5 For group 3, the Switch will report ON/OFF status of Relay2.
- 4 / 5 For group 4, the Switch will report Instant Power Consumption (Watt) and Accumulated Power Consumption (KWh) of Relay1.
- 5 / 5 For group 5, the Switch will report Instant Power Consumption (Watt) and Accumulated Power Consumption (KWh) of Relay2.

### Supported Command Classes (20):

Association Group Information V3	Association V2
Basic V2	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V5
Indicator V3	Manufacturer Specific V2
Meter V5	Multi-Channel Association V3
Multi-Channel V4	Notification V8
Powerlevel	Security S0
Security S2	Supervision
Switch Binary V2	Transport Service V2
Version V3	Z-Wave Plus Info V2