

Z-Wave Protocol Implementation Conformance Statement

Mini SmartPlug Dimmer

General Information

| | |
|--------------------------------|----------------|
| Product Identifier: | N4002 |
| Brand Name: | NEW ONE |
| Product Version: | HW: 1 FW: 1.00 |
| Z-Wave Certification #: | ZC12-21080303 |

Product Features

| | |
|-----------------------------------|------------------------------|
| Color | White |
| Electric Load Type | Dimmable LED Incandescent |
| Firmware Updatable | Updatable by Consumer by RF |
| Switch Load Capacity Watts | 400W |

Z-Wave Product Information

| | |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | No |
| Supports Security S2? | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|-------------------------------------|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x4002 |
| Z-Wave Product Type: | 0xAC01 |
| Z-Wave Hardware Platform: | ZGM130 |
| Z-Wave Development Kit Version: | 7.13.6 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Multilevel Switch / Always On Slave |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Mini SmartPlug Dimmer

Association Group Information

Group # / Max Description

Nodes

| | |
|-------|-------------------|
| 1 / 5 | Z-Wave Lifeline |
| 2 / 5 | BASIC SET COMMAND |
| 3 / 5 | BASIC SET COMMAND |

Supported Command Classes (17):

| | |
|----------------------------------|------------------------------|
| Association Group Information V3 | Association V3 |
| Basic V2 | Central Scene V3 |
| Configuration V4 | Device Reset Locally |
| Firmware Update Meta-Data V5 | Indicator V3 |
| Manufacturer Specific V2 | Multi-Channel Association V3 |
| Powerlevel | Security S2 |
| Supervision | Switch Multilevel V4 |
| Transport Service V2 | Version V3 |
| Z-Wave Plus Info V2 | |