

## Z-Wave Protocol Implementation Conformance Statement

### 4 in 1 PIR Sensor

#### General Information

<b>Product Identifier:</b>	ZP3113BR-7
<b>Brand Name:</b>	Vision
<b>Product Version:</b>	HW: 3 FW: 32.32
<b>Z-Wave Certification #:</b>	ZC12-21100319

#### Product Features

<b>Firmware Updatable</b>	Not Updatable
---------------------------	---------------

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Australia / New Zealand, Malaysia, Brazil
<b>Z-Wave Product ID:</b>	0x2112
<b>Z-Wave Product Type:</b>	0x2021
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 5	Group 1 = Lifeline (Battery, Reset Locally, Indicator, Notification)
2 / 5	Group 2 = ON/OFF Control (Basic Set)

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 4 in 1 PIR Sensor

### Supported Command Classes (20):

Application Status	Association Group Information V3
Association V2	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S0	Security S2
Sensor Multilevel V11	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2