

## Z-Wave Protocol Implementation Conformance Statement

# In-Wall Tamper Resistant Smart Outlet

### General Information

|                                |                  |
|--------------------------------|------------------|
| <b>Product Identifier:</b>     | 61304/ZW1002     |
| <b>Brand Name:</b>             | iDevices         |
| <b>Product Version:</b>        | HW: 255 FW: 5.51 |
| <b>Z-Wave Certification #:</b> | ZC10-21107057    |

### Product Features

|                                     |                             |
|-------------------------------------|-----------------------------|
| <b>Firmware Updatable</b>           | Updatable by Consumer by RF |
| <b>Neutral Wire Required</b>        | Yes                         |
| <b>Switch Load Capacity Current</b> | 15A                         |
| <b>Switch Load Capacity Watts</b>   | 1800W                       |
| <b>Switch Type</b>                  | Push Button Illuminated     |

### Z-Wave Product Information

|                                      |   |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology?  | Yes                                       |
| Supports Z-Wave Network Security?    | Yes                                       |
| Supports Z-Wave AES-128 Security S0? | No  |
| Supports Security S2?                | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible?               | Yes                                       |

### Z-Wave Technical Information

|  |                                       |
|--|---------------------------------------|
| <b>Z-Wave Frequency:</b>               | U.S. / Canada / Mexico                |
| <b>Z-Wave Product ID:</b>              | 0x3235                                |
| <b>Z-Wave Product Type:</b>            | 0x4952                                |
| <b>Z-Wave Hardware Platform:</b>       | ZM5202                                |
| <b>Z-Wave Development Kit Version:</b> | 6.82.00                               |
| <b>Z-Wave Library Type:</b>            | Enhanced 232 Slave                    |
| <b>Z-Wave Device Type / Role Type:</b> | On/Off Power Switch / Always On Slave |

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-Wall Tamper Resistant Smart Outlet

### Association Group Information

**Group # / Max    Description**

**Nodes**

- 1 / 5            Z-Wave Plus Lifeline
- 2 / 5            Association Group 2 supports basic set and is controlled by single pressing the button
- 3 / 5            Association Group 3 supports basic set and is controlled by double pressing the button

**Supported Command Classes (18):**

- |                          |                              |
|--------------------------|------------------------------|
| Application Status       | Association Group Info       |
| Association V2           | Basic V2                     |
| Central Scene V3         | Configuration V4             |
| Device Reset Locally     | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Powerlevel                   |
| Scene Activation         | Scene Actuator Conf          |
| Security S2              | Supervision                  |
| Switch Binary V2         | Transport Service V2         |
| Version V3               | Z-Wave Plus Info V2          |

**Controlled Command Classes (1):**

- Basic V2