

## Z-Wave Protocol Implementation Conformance Statement

### Dimmer-Control

#### General Information

<b>Product Identifier:</b>	FGD-212
<b>Brand Name:</b>	Nice
<b>Product Version:</b>	HW: 2 FW: 3.05:03.05
<b>Z-Wave Certification #:</b>	ZC10-22037071

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1000
<b>Z-Wave Product Type:</b>	0x0102
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 1	"Lifeline" reports the device status and allows for assigning single device only (main controller by default).
2 / 8	"On/Off (S1)" is used to turn the associated devices on/off.
3 / 8	"Dimmer (S1)" is used to set the associated devices to a certain level.
4 / 8	"On/Off (S2)" is used to turn the associated devices on/off.
5 / 8	"Dimmer (S2)" is used to set the associated devices to a certain level.

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Dimmer-Control

### Supported Command Classes (21):

Application Status	Association Group Info
Association V2	Basic
Configuration	CRC-16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Meter V3
Multi Channel Association V3	Multi Channel V4
Notification V5	Powerlevel
Protection V2	Security 0
Sensor Multilevel V4	Switch All
Switch Multilevel V3	Version V2
Z-Wave Plus Info V2	

### Controlled Command Classes (3):

Basic	Scene Activation
Switch Multilevel V3	