

## Z-Wave Protocol Implementation Conformance Statement

### RGBW-Control

#### General Information

<b>Product Identifier:</b>	FGRGBW-442
<b>Brand Name:</b>	Nice
<b>Product Version:</b>	HW: 2 FW: 5.00:05.00:01.00
<b>Z-Wave Certification #:</b>	ZC10-22047077

#### Product Features

<b>Color</b>	White
--------------	-------

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1000
<b>Z-Wave Product Type:</b>	0x0902
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Multilevel Switch - Color Tunable Multilevel / Always On Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 1	"Lifeline" reports the device status and allows for assigning single device only (main controller by default).
2 / 5	"RGBW Sync" allows to synchronize state of other RGBW-Control devices.
3 / 5	"On/Off (S1)" is used to turn the associated devices on/off reflecting S1 operation.
4 / 5	"Dimmer (S1)" is used to change level of associated devices reflecting S1 operation.

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## RGBW-Control

- 5 / 5 "On/Off (S2)" is used to turn the associated devices on/off reflecting S2 operation.
- 6 / 5 "Dimmer (S2)" is used to change level of associated devices reflecting S2 operation.
- 7 / 5 "On/Off (S3)" is used to turn the associated devices on/off reflecting S3 operation.
- 8 / 5 "Dimmer (S3)" is used to change level of associated devices reflecting S3 operation.
- 9 / 5 "On/Off (S4)" is used to turn the associated devices on/off reflecting S4 operation.
- 10 / 5 "Dimmer (S4)" is used to change level of associated devices reflecting S4 operation.

### Supported Command Classes (23):

Application Status	Association Group Information V2
Association V2	Central Scene V3
Color Switch V3	Configuration
CRC-16 Encapsulation	Device Reset Locally
Firmware Update Meta Data V4	Manufacturer Specific V2
Meter V3	Multi Channel Association V3
Multi Channel V4	Multilevel Sensor V11
Notification V8	Powerlevel
Protection V2	Security 0
Security 2	Supervision
Transport Service V2	Version V2
Z-Wave Plus Info V2	

### Controlled Command Classes (1):

Color Switch V3