

## Z-Wave Protocol Implementation Conformance Statement

# Smart In Wall Dimmer & Switch

### General Information

<b>Product Identifier:</b>	HS-WX300-R2
<b>Brand Name:</b>	HomeSeer
<b>Product Version:</b>	HW: 02 FW: 02.01
<b>Z-Wave Certification #:</b>	ZC14-22120183

### Product Features

<b>Color</b>	White
<b>Electric Load Type</b>	Dimmable Fluorescent Dimmable LED Incandescent LED
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Neutral Wire Required</b>	Yes
<b>Outdoor Use</b>	Yes
<b>Z-Wave Scene Type</b>	Scene & Central Scene
<b>Switch Load Capacity Watts</b>	Dimmable LED/CFL: 300W, Incandescent: 600W

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart In Wall Dimmer & Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x4036
<b>Z-Wave Product Type:</b>	0x4447
<b>Z-Wave Hardware Platform:</b>	EFR32ZG23A
<b>Z-Wave Development Kit Version:</b>	7.18.1
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Multilevel Switch DT / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5

2 / 5

**Supported Command Classes (17):**

Association Group Information (AGI) V3	Association V2
Basic V2	Central Scene V3
Configuration V4	Device Reset Locally
Firmware Update Meta Data V5	Indicator V3
Manufacturer Specific V2	Multi Channel Association V3
Multilevel Switch V4	Powerlevel
Security 2	Supervision
Transport Service V2	Version V3
Z-Wave Plus Info V2	