



Z-Wave Protocol Implementation Conformance Statement

Double Relay

General Information

| | |
|--------------------------------|------------------|
| Product Identifier: | ZEN52 LR |
| Brand Name: | ZOOZ |
| Product Version: | HW: 01 FW: 01.50 |
| Z-Wave Certification #: | ZC14-23020193 |

Product Features

| | |
|------------------------------|-----------------------------|
| Firmware Updatable | Updatable by Consumer by RF |
| Loads Controlled | 2 |
| Neutral Wire Required | Yes |
| Z-Wave Scene Type | Central Scene |

Z-Wave Product Information

| | |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | No |
| Supports Security S2? | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|------------------------------------|
| Z-Wave Frequency: | U.S. / Canada / Mexico, US_LR |
| Z-Wave Product ID: | 0x0202 |
| Z-Wave Product Type: | 0x0904 |
| Z-Wave Hardware Platform: | ZGM130S037HGN2 / ZGM130S037HGN1 |
| Z-Wave Development Kit Version: | 7.15.4 |
| Z-Wave Library Type: | Enhanced End Node 232 |
| Z-Wave Device Type / Role Type: | Binary Switch DT / Always On Slave |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Double Relay

Association Group Information

Group # / Max Description

Nodes

1 / 5

2 / 5

3 / 5

Supported Command Classes (19):

| | |
|------------------------------|--|
| Application Status | Association Group Information (AGI) V3 |
| Association V2 | Basic V2 |
| Binary Switch V2 | Central Scene V3 |
| Configuration V4 | Device Reset Locally |
| Firmware Update Meta Data V5 | Indicator V3 |
| Manufacturer Specific V2 | Multi Channel Association V3 |
| Multi Channel V4 | Powerlevel |
| Security 2 | Supervision |
| Transport Service V2 | Version V3 |
| Z-Wave Plus Info V2 | |