

# manual

---

## Temperature sensor

Item: 51112

EN

NO

SV

**CLEVERIO**  
SMARTHOME

[www.cleverio.se](http://www.cleverio.se)

Box 50435, Malmö, Sweden

2019-03-20



**Specifications**

Battery	1x CR2450
Protocol	Z-Wave Plus
Working temperature	-10 °C to 60 °C
Temp. measurement	-10 °C to 60 °C
Humidity measurement	Max 95%
Size	65x60x20.8 mm

**Device Add for Inclusion**

–Press the Net\_Button 3 times within 1.5s, Green LED is Blinking 3 times within 1 second.

–If Inclusion Process is successful, Green LED will turn off.

**Device Remove for Exclusion**

–Press the Net\_Button 3 times within 1.5s.

–If Exclusion Process is successful, Green LED is Blinking 6 times, then turn off.

**Device Remove for Exclusion**

–Press the Net\_Button 3 times within 1.5s.

–If Exclusion Process is successful, Green LED is Blinking

6 times, then turn off.

## **Device Factory Reset**

- Long press Net\_Button at least 10 seconds in the product.
- Device Reset Locally notification is Transmitted.
- Please use this procedure only when the network primary controller is missing or otherwise inoperable.

## **Association & Association Group Information**

- Lifeline between controller and the product
- Supported command classes

Battery Report, Multilevel Sensor Report, and Device Reset Locally notification.

- Association Group description

>>Association group 1: Lifeline association group

Maximum supported node is 5

Include command classes: Battery report, multilevel sensor report, and Device Reset Locally