

## Z-Wave Protocol Implementation Conformance Statement

### Siren Gen5

#### General Information

<b>Product Identifier:</b>	ZW080-A17
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 50 FW: 3.25
<b>Z-Wave Certification #:</b>	ZC10-14090012

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0050
<b>Z-Wave Product Type:</b>	0x0104
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Siren / Always On Slave

#### Association Group Information

##### Group # / Max Description

##### Nodes

1 / 5	Group 1 is assigned to the Lifeline association group and every device has 5 nodes to associate. When the Siren is received the commands sent by controller to be turned on or off, the Siren will send a basic report of its status to the nodes in association group 1. To change what kind of signal is sent to the nodes in group 1, please see the detailed description of configuration parameter 80.
-------	---

##### Controlled Command Classes (2):

Hail	Scene Activation
------	------------------