

## Z-Wave Protocol Implementation Conformance Statement

# Harmony Home Hub Extender

### General Information

<b>Product Identifier:</b>	N-R0009
<b>Brand Name:</b>	Logitech
<b>Product Version:</b>	001
<b>Z-Wave Certification #:</b>	ZC10-15050017

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5304
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Static Controller
<b>Z-Wave Device Type / Role Type:</b>	Gateway / Central Static Controller

### Association Group Information

Group # / Max Nodes	Description
1 / 5	Z-Wave Plus Lifeline

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Harmony Home Hub Extender

### Controlled Command Classes (28):

Application Status	Association
Association Group Information V1	Basic
Battery	Controller Replication
CRC16 Encapsulation	Door Lock
Manufacturer Specific	Multi-Channel Association V1
Multi-Channel V1	Network Management Basic
Network Management Inclusion	Network Management Primary
No Operation	Notification V1
Security S0	Sensor Binary
Switch Binary	Switch Multilevel
Thermostat Fan Mode	Thermostat Fan State
Thermostat Mode	Thermostat Operating State
Thermostat Setpoint	Version
Wake Up	Z-Wave Plus Info