

## Z-Wave Protocol Implementation Conformance Statement

# Smart Energy In Wall Meter

### General Information

<b>Product Identifier:</b>	PAB01-1
<b>Brand Name:</b>	Philio
<b>Product Version:</b>	01
<b>Z-Wave Certification #:</b>	ZC10-16010004

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x001A
<b>Z-Wave Product Type:</b>	0x0006
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Whole Home Meter - Simple / Always On Slave

### Association Group Information

Group # / Max Nodes	Description
1 / 1	Z-Wave Plus Lifeline For group 1, the Switch will report (1) Instant Power Consumption (Watt) read from CT1 (2) Accumulated Power Consumption (KWh) read from CT1.
2 / 1	For group 2, the Switch will report (1) Instant Power Consumption (Watt) read from CT2 (2) Accumulated Power Consumption (KWh) read from CT2.
3 / 1	For group 3, the Switch will report (1) The sum of instant Power Consumption (Watt) read from CT1 and CT2 (2) The sum of accumulated Power Consumption (KWh) read from CT1 and CT2.