



Z-Wave Protocol Implementation Conformance Statement

FIBARO Wall Plug E/F

General Information

Product Identifier: FGWPE/F-102
Brand Name: FIBARO
Product Version: HW: 2 FW: 3.15:03.02
Z-Wave Certification #: ZC10-16035016

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: CEPT (Europe)
Z-Wave Product ID: 0x1001
Z-Wave Product Type: 0x0602
Z-Wave Hardware Platform: ZM5202
Z-Wave Development Kit Version: 6.51.06
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: On/Off Power Switch / Always On Slave

Association Group Information

| Group # / Max | Description |
|---------------|---|
| Nodes | |
| 1 / 1 | “Lifeline” reports the device status and allows for assigning single device only (main controller by default). |
| 2 / 10 | “On/Off (button)” devices in this group will be switched on or off when relay status is changed using the B-button (done via BASIC SET command frames). |
| 3 / 10 | “On/Off (power)” devices in this group will be switched on or off depending on the current load (done via BASIC SET command frames). |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

FIBARO Wall Plug E/F

Supported Command Classes (18):

| | |
|--|-------------------------------------|
| Association Group Information V1 | Command Class Application Status |
| Command Class Association V2 | Command Class Basic |
| Command Class Configuration | Command Class CRC16 Encap |
| Command Class Device Reset Locally | Command Class Firmware Update Md V3 |
| Command Class Manufacturer Specific V2 | Command Class Meter V2 |
| Command Class Multi Channel Association V3 | Command Class Notification V5 |
| Command Class Powerlevel | Command Class Security |
| Command Class Sensor Multilevel V5 | Command Class Switch Binary |
| Command Class Version V2 | Command Class Z-Wave+ Info V2 |

Controlled Command Classes (2):

| | |
|---------------------|--------------------------------|
| Command Class Basic | Command Class Multi Channel V4 |
|---------------------|--------------------------------|