

## Z-Wave Protocol Implementation Conformance Statement

### In Wall Single relay(1way) switch module

#### General Information

<b>Product Identifier:</b>	PAN05-1B
<b>Brand Name:</b>	Philio
<b>Product Version:</b>	HW: 1 FW: 1.12
<b>Z-Wave Certification #:</b>	ZC10-16025010

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0010
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max Nodes	Description
1 / 1	Z-Wave Plus Lifeline The Switch can be set to send reports to associated Z-Wave devices. It supports only one association group and the group has one node support. Group1 support SWITCH_BINARY_REPORT. For group 1, the Switch will report ON/OFF status of Relay to controller.