



## Z-Wave Protocol Implementation Conformance Statement

### Door Sensor

#### General Information

**Product Identifier:** NAS-DS01Z  
**Brand Name:** Coolcam  
**Product Version:** 41  
**Z-Wave Certification #:** ZC10-16020010

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology? No  
 Supports Z-Wave Network Security? Yes  
 Supports Z-Wave AES-128 Security S0? No  
 Supports Security S2? No  
 SmartStart Compatible? No

#### Z-Wave Technical Information

**Z-Wave Frequency:** U.S. / Canada / Mexico  
**Z-Wave Product ID:** 0x0082  
**Z-Wave Product Type:** 0x0003  
**Z-Wave Hardware Platform:** ZM5202  
**Z-Wave Development Kit Version:** 6.51.06  
**Z-Wave Library Type:** Routing Slave  
**Z-Wave Device Type / Role Type:** Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

Group # / Max Nodes	Description
1 / 4	<p>Every group can be support to associated 5 devices max. GROUP 1 is lifeline service that assigned to Sensor (Door/Window detector) status – Open/Close. It enables the sensor to send reports and readings to Z-Wave Controller or Z-Wave Gateway whenever the sensor is triggered. This Group Support: NOTIFICATION_REPORT BATTERY_REPORT SENSOR_BINARY_REPORT DEVICE_RESET_LOCALLY_NOTIFICATION GROUP 2 allows for sending control commands to associated devices such as relay module, lighting, etc. This association group is configured through the advanced parameters no. 1 and 2. This Group Support: BASIC_SET. GROUP 3 allows for Send Notification to associated devices in this group. This Group Support: NOTIFICATION_REPORT GROUP 4 allows for Send Notification to associated devices in this group. This Group Support: SENSOR_BINARY_REPORT</p>

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Door Sensor

### Supported Command Classes (12):

Association Group Information V1	Command Class Association
Command Class Battery	Command Class Configuration
Command Class Device Reset Locally	Command Class Manufacturer Specific
Command Class Notification V1	Command Class Powerlevel
Command Class Sensor Binary	Command Class Version
Command Class Wake Up	Command Class Z-Wave+ Info

### Controlled Command Classes (1):

Command Class Basic