

Z-Wave Protocol Implementation Conformance Statement

Wall Plug

General Information

Product Identifier:	NAS-WR01Z
Brand Name:	Coolcam
Product Version:	41
Z-Wave Certification #:	ZC10-16020013

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0087
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 3	Associations Through an association this Plug may control another Z-Wave network device, e.g. a alarm device, wall plug, lighting etc. The Wall Plug provides three association groups, and every group can be support to associated 5 devices max. GROUP 1 is lifeline service that assigned to plug status – ON/OFF. It enables the Plug to send reports and readings to Z-Wave Controller or Z-Wave Gateway. This Group Support: NOTIFICATION_REPORT_V4 COMMAND_CLASS_METER_V4 COMMAND_CLASS_SWITCH_BINARY DEVICE_RESET_LOCALLY_NOTIFICATION GROUP 2 allows for sending control commands to associated devices such as Siren, relay module, lighting, etc. If current load is over the max current defined in parameter #3, the Plug will send a BASIC_SET (0xFF) to associated devices. When current load is normal, plug will send a BASIC_SET (0x00) to associated devices. This Group Support: BASIC_SET GROUP 3 allows for Send
-------	---

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Wall Plug