

Z-Wave Protocol Implementation Conformance Statement

Alarm.com Interlogix Simon XT/i Radio Module

General Information

| | |
|--------------------------------|------------------------|
| Product Identifier: | ADC-200H-EVD |
| Brand Name: | Alarm.com |
| Product Version: | HW: 115 FW: 4.32:03.04 |
| Z-Wave Certification #: | ZC10-16045033 |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | No |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|--|--|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x0101 |
| Z-Wave Product Type: | 0x0001 |
| Z-Wave Hardware Platform: | ZM5202 |
| Z-Wave Development Kit Version: | 6.51.06 |
| Z-Wave Library Type: | Static Controller |
| Z-Wave Device Type / Role Type: | Central Controller / Central Static Controller |

Association Group Information

| Group # / Max Nodes | Description |
|---------------------|---|
| 1 / 56 | Z-Wave Plus Lifeline - when the controller is reset (new home id, etc) it will send a DEVICE_RESET_LOCALLY_NOTIFICATION to all associated nodes |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Alarm.com Interlogix Simon XT/i Radio Module

Controlled Command Classes (35):

| | |
|---------------------------|----------------------------------|
| Alarm | Association Group Information V1 |
| Association V2 | Basic |
| Battery | Clock |
| Configuration | CRC16 Encapsulation |
| Device Reset Locally | Door Lock |
| Firmware Update Meta-Data | Manufacturer Specific |
| Meter | Multi-Channel Association V3 |
| Multi-Channel V4 | No Operation |
| Notification V3 | Powerlevel |
| Schedule Entry Lock V3 | Security S0 |
| Sensor Binary | Sensor Multilevel |
| Switch Binary | Switch Multilevel |
| Thermostat Fan Mode | Thermostat Fan State |
| Thermostat Mode | Thermostat Operating State |
| Thermostat Setback | Thermostat Setpoint |
| Time Parameters | User Code |
| Version V2 | Wake Up V2 |
| Z-Wave Plus Info V2 | |