

Z-Wave Protocol Implementation Conformance Statement

FIBARO Dimmer 2

General Information

Product Identifier:	FGD-212
Brand Name:	FIBARO
Product Version:	HW: 2 FW: 3.05:03.05
Z-Wave Certification #:	ZC10-16045036

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1000
Z-Wave Product Type:	0x0102
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max Nodes	Description
1 / 1	Z-Wave Plus Lifeline. Type of frame sent by the device when the association group is activated: SWITCH_MULTILEVEL_REPORT; DEVICE_RESET_LOCALLY_NOTIFICATION; SCENE_ACTIVATION_SET; METER_REPORT; SENSOR_MULTILEVEL_REPORT; NOTIFICATION REPORT.
2 / 8	Association Group „On/Off (S1)“ is assigned to key no. 1. Type of frame sent by the device when the association group is activated: BASIC_SET.
3 / 8	Association Group „Dimmer (S1)“ is assigned to key no. 1. Type of frame sent by the device when the association group is activated: SWITCH_MULTILEVEL_SET.
4 / 8	Association Group „On/Off (S2)“ is assigned to key no. 2. Type of frame sent by the device when the

Z-Wave Protocol Implementation Conformance Statement

(Continued)

FIBARO Dimmer 2

5 / 8 Association Group „Dimmer (S2)” is assigned to key no. 2. Type of frame sent by the device when the association group is activated: SWITCH_MULTILEVEL_SET.

Controlled Command Classes (3):

Basic

Scene Activation

Switch Multilevel V3