

Z-Wave Protocol Implementation Conformance Statement

FIBARO Swipe

General Information

Product Identifier:	FGGC-001
Brand Name:	FIBARO
Product Version:	HW: 1 FW: 3.02:03.11
Z-Wave Certification #:	ZC10-16045047

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x3000
Z-Wave Product Type:	0x0D01
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Wall Controller / Portable Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	“Lifeline” reports the device status and allows for assigning single device only (main controller by default).
2 / 5	“Flick UP” is assigned to moving the hand up over the panel (sends Basic Set command frames).
3 / 5	“Flick DOWN” is assigned to moving the hand down over the panel (sends Basic Set command frames).
4 / 5	“Flick LEFT” is assigned to moving the hand from the right to the left side of the panel (sends Basic Set command frames).
5 / 5	“Flick RIGHT” is assigned to moving the hand from the left to the right side of the panel (sends Basic Set command frames) .

Z-Wave Protocol Implementation Conformance Statement

(Continued)

FIBARO Swipe

6 / 5 “Circular AirWheel” is assigned to circular move of the hand clockwise or counter-clockwise over the panel
(sends Switch Multilevel Start/Stop Level Change command frames).

Controlled Command Classes (3):

Basic

Central Scene V2

CRC16 Encapsulation