

Z-Wave Protocol Implementation Conformance Statement

Smart Power Plug

General Information

Product Identifier:	NAS-WR01Z
Brand Name:	Coolcam
Product Version:	HW: 65 FW: 3.70
Z-Wave Certification #:	ZC10-16055074

Product Features

Color	White
Firmware Updatable	Updatable by Manufacturer
Switch Load Capacity Volt-Ampere	12A 220V
Switch Type	Push Button

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1087
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Power Plug

- 2 / 5 GROUP 2 allows for sending control commands to associated devices such as Siren, relay module, lighting, etc. If current load is over the max current defined in parameter #3, the Plug will send a BASIC_SET (0xFF) to associated devices. When current load is normal, plug will send a BASIC_SET (0x00) to associated devices.
This Group Support: BASIC_SET
- 3 / 5 GROUP 3 allows for Send Notification to associated devices in this group. This Group Support:
NOTIFICATION_REPORT_V4

Controlled Command Classes (1):

Basic