

## Z-Wave Protocol Implementation Conformance Statement

# 10 Year Smoke Detector and Siren

### General Information

<b>Product Identifier:</b>	200940US
<b>Brand Name:</b>	Z-Wave.Me
<b>Product Version:</b>	HW: 1 FW: 1.02
<b>Z-Wave Certification #:</b>	ZC10-16055070

### Product Features

<b>Battery Quantity</b>	1
<b>Battery Type</b>	CR2
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Outdoor Use</b>	No
<b>Sensors</b>	Smoke Density

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0x04
<b>Z-Wave Product Type:</b>	0x0x04
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 10 Year Smoke Detector and Siren

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 10            Z-Wave Plus Lifeline

2 / 10            Alarm Reports. All devices in this group will receive Alarm notifications (Smoke , Battery Low, Tamper)

3 / 10            Switching Command. All devices in this group will receive a BASIC SET command on Smoke Alarms.  
Configuration parameter 3 and 4 will define when ON and when OFF is sent.

**Controlled Command Classes (1):**

Basic