

Z-Wave Protocol Implementation Conformance Statement

Smart Motion Sensor

General Information

Product Identifier:	HS1MS-Z
Brand Name:	HEIMAN
Product Version:	HW: 255 FW: 1.25
Z-Wave Certification #:	ZC10-16055092

Product Features

Battery Type	CR123A
Color	White
Firmware Updatable	Not Updatable
Outdoor Use	Yes
Sensors	Motion/No Motion (Binary)
Battery Quantity	1

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1000
Z-Wave Product Type:	0x8001
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Routing Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Motion Sensor

Association Group Information

Group # / Max **Description**

Nodes

- | | |
|-------|--|
| 1 / 5 | Root Device group(Notification) 1-Report status of people passing by, no people passing by, tamper alarm and tamper recovery through lifeline. 2- When the Device detects new event of people passing by or no people passing by, tamper alarm and tamper recovery, the device will be triggered. |
| 2 / 5 | Lifeline association group Include command classe: Battery report, Notification report, and Device Reset Locally notification, Binary report. |
| 3 / 5 | Root Device group(Binary Sensor) Binary Sensor Command Class:Compatible with 300 series. 1-Report status of people passing by, no people passing by, tamper alarm and tamper recovery via lifeline. 2- When the Device detects new event of people passing by or no people passing by, tamper alarm and tamper recovery, the device will be triggered. |