

Z-Wave Protocol Implementation Conformance Statement

MultiSensor 6

General Information

| | |
|--------------------------------|------------------|
| Product Identifier: | ZW100-A |
| Brand Name: | Aeotec |
| Product Version: | HW: 100 FW: 1.08 |
| Z-Wave Certification #: | ZC10-16065112 |

Product Features

| | |
|--------------------------------------|--|
| Battery Quantity | 2 |
| Battery Type | CR123A |
| Firmware Updatable | Updatable by Consumer by RF |
| IP (Ingress Protection) Rated | Yes |
| Sensors | Air Temperature Humidity Luminance Motion/No Motion (Binary) Ultraviolet Index Vibration/Shock (Binary) |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | No |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

MultiSensor 6

Z-Wave Technical Information

| | |
|--|--|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x0064 |
| Z-Wave Product Type: | 0x0102 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.51.06 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Multilevel Sensor / Reporting Sleeping Slave |

Association Group Information

| Group # / Max | Description |
|----------------------|--------------------|
|----------------------|--------------------|

Nodes

| | |
|-------|--|
| 1 / 5 | The MultiSensor supports 1 association group. Group 1 is assigned to the Lifeline association group and can add max 5 association nodes. When the PIR motion sensor is triggered, the MultiSensor will send Basic Set (0xFF) to the associated nodes. If no PIR motion is triggered after the PIR interval time (configurable), the MultiSensor will send Basic Set (0x00) to the associated nodes. The automatically reports of temperature, humidity, luminance and ultraviolet (configurable) also can be sent to the associated nodes. |
|-------|--|