

Z-Wave Protocol Implementation Conformance Statement

MultiSensor 6

General Information

Product Identifier:	ZW100-C
Brand Name:	Aeotec
Product Version:	HW: 100 FW: 1.08
Z-Wave Certification #:	ZC10-16065113

Product Features

Battery Quantity	2
Battery Type	CR123A
Firmware Updatable	Updatable by Consumer by RF
IP (Ingress Protection) Rated	Yes
Sensors	Air Temperature Humidity Luminance Motion/No Motion (Binary) Ultraviolet Index Vibration/Shock (Binary)

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

MultiSensor 6

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0064
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Multilevel Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
----------------------	--------------------

Nodes

1 / 5	The MultiSensor supports 1 association group. Group 1 is assigned to the Lifeline association group and can add max 5 association nodes. When the PIR motion sensor is triggered, the MultiSensor will send Basic Set (0xFF) to the associated nodes. If no PIR motion is triggered after the PIR interval time (configurable), the MultiSensor will send Basic Set (0x00) to the associated nodes. The automatically reports of temperature, humidity, luminance and ultraviolet (configurable) also can be sent to the associated nodes.
-------	--

Controlled Command Classes (1):

Basic