



## Z-Wave Protocol Implementation Conformance Statement

### Z-Uno

#### General Information

<b>Product Identifier:</b>	v3
<b>Brand Name:</b>	Z-Wave.Me
<b>Product Version:</b>	HW: 1 FW: 0.70
<b>Z-Wave Certification #:</b>	ZC10-16065104

#### Product Features

<b>Communications Connections</b>	USB (Universal Serial Bus)
<b>Firmware Updatable</b>	Updatable by Consumer by Wire
<b>Sensors</b>	Air Temperature Carbon Dioxide Carbon Monoxide Freeze Heat Humidity Luminance Moisture Motion/No Motion (Binary) Open/Closed (Binary) Smoke Density Vibration/Shock (Binary) Water Flow

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Uno

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0110
<b>Z-Wave Hardware Platform:</b>	WML-C85
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max**    **Description**

#### Nodes

1 / 5	Z-Wave Plus Lifeline. All unsolicited reports on all channels are sent to this group
2 / 5	Configurable group to send on/off, dimming or scene activation. See product reference
3 / 5	Configurable group to send on/off, dimming or scene activation. See product reference
4 / 5	Configurable group to send on/off, dimming or scene activation. See product reference
5 / 5	Configurable group to send on/off, dimming or scene activation. See product reference
6 / 5	Configurable group to send on/off, dimming or scene activation. See product reference

#### Supported Command Classes (16):

Association Group Information V1	Command Class Association V2
Command Class Basic	Command Class Configuration
Command Class Device Reset Locally	Command Class Firmware Update Md V3
Command Class Manufacturer Specific V2	Command Class Multi Channel V4
Command Class Notification V5	Command Class Powerlevel
Command Class Security	Command Class Sensor Binary V2
Command Class Sensor Multilevel V7	Command Class Switch Multilevel
Command Class Version V2	Command Class Z-Wave+ Info V2

#### Controlled Command Classes (4):

Command Class Basic	Command Class Multi Channel V4
Command Class Security	Command Class Switch Multilevel