

Z-Wave Protocol Implementation Conformance Statement

LED Bulb

General Information

Product Identifier:	ZW098-B55
Brand Name:	Aeotec
Product Version:	HW: 98 FW: 1.05
Z-Wave Certification #:	ZC10-16075130

Product Features

Switch Type	Toggle
Z-Wave Scene Type	Scene
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x0062
Z-Wave Product Type:	0x0203
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max Nodes	Description
----------------------------	--------------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

LED Bulb

2 / 5 In this group, the Basic Set, Switch Binary Set, Switch Multilevel Start Level Change, Switch Multilevel Stop Level Change, Switch Multilevel Set, Scene Activation Set commands would be sent to the associated nodes in association group 2 when the Bulb receives the Basic Set, Switch Binary Set, Switch Multilevel Start Level Change, Switch Multilevel Stop Level Change, Switch Multilevel Set, Scene Activation Set commands from the main controller.

Controlled Command Classes (2):

Basic

Hail