



## Z-Wave Protocol Implementation Conformance Statement

### MIMO2+

#### General Information

<b>Product Identifier:</b>	MIMO2+
<b>Brand Name:</b>	FortrezZ LLC
<b>Product Version:</b>	HW: 5 FW: 2.08
<b>Z-Wave Certification #:</b>	ZC10-16075155

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Current</b>	10A / 24VDC (Relays)
<b>Switch Load Capacity Volt-Ampere</b>	16V (Inputs / Signal), 24V (Outputs / Relays)
<b>Sensors</b>	Motion/No Motion (Binary) Open/Closed (Binary)
<b>Switch Type</b>	Dry Contact

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

MIMO2+

## Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0204
<b>Z-Wave Product Type:</b>	0x0463
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.08
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Multilevel Sensor / Always On Slave

## Association Group Information

**Group # / Max    Description**

### Nodes

1 / 2	Z-Wave Plus Lifeline
2 / 2	SIG1 (Basic Set) - Upon change of trigger
3 / 2	SIG2 (Basic Set) - Upon change of trigger

### Supported Command Classes (17):

Association Group Information V1	Command Class Alarm V2
Command Class Association V2	Command Class Basic
Command Class Configuration	Command Class Device Reset Locally
Command Class Firmware Update Md V2	Command Class Manufacturer Specific V2
Command Class Multi Channel Association V3	Command Class Multi Channel V4
Command Class Powerlevel	Command Class Security
Command Class Sensor Multilevel	Command Class Sensor Multilevel V9
Command Class Switch Binary	Command Class Version V2
Command Class Z-Wave+ Info V2	

### Controlled Command Classes (1):

Command Class Basic