

## Z-Wave Protocol Implementation Conformance Statement

# EA-3 Entertainment and Automation Controller with US Z-Wave Mod

### General Information

<b>Product Identifier:</b>	EA-3 / C4-ZWU
<b>Brand Name:</b>	Control4
<b>Product Version:</b>	HW: 4 FW: 4.24:02.144
<b>Z-Wave Certification #:</b>	ZC10-16085186

### Product Features

<b>Color</b>	White
<b>Communications Protocol</b>	Z-Wave Serial API
<b>Controller Supports Multiple Z-Wave Interfaces</b>	No
<b>Communications Connections</b>	Manufacturer Proprietary
<b>Controller Supports Multiple Networks</b>	No
<b>Firmware Updatable</b>	Updatable by Manufacturer

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x002B
<b>Z-Wave Product Type:</b>	0x0000
<b>Z-Wave Hardware Platform:</b>	ZM5304
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Static Controller

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## EA-3 Entertainment and Automation Controller with US Z-Wave Module

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 1                    Z-Wave Plus Lifeline; Device reset local

**Supported Command Classes (10):**

Application Status	Association Group Info
Association V2	CRC16 Encapsulation
Device Reset Locally	Manufacturer Specific
Powerlevel	Security S0
Version V2	Z-Wave Plus Info V2

**Controlled Command Classes (18):**

Association Group Info	Association V2
Basic	Battery
Configuration	CRC16 Encapsulation
Manufacturer Specific	Multi-Channel Association V3
Multi-Channel V4	Notification V3
Security S0	Sensor Binary
Sensor Multilevel	Switch Binary
Switch Multilevel	Version V2
Wake Up V2	Z-Wave Plus Info V2