

## Z-Wave Protocol Implementation Conformance Statement

### 1000W Dimmer

#### General Information

<b>Product Identifier:</b>	DZ1KD
<b>Brand Name:</b>	Leviton Manufacturing, Inc.
<b>Product Version:</b>	HW: 255 FW: 1.22
<b>Z-Wave Certification #:</b>	ZC10-16095222

#### Product Features

<b>Color</b>	White
<b>Electric Load Type</b>	Dimmable LED Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Watts</b>	1000W
<b>Neutral Wire Required</b>	Yes
<b>Switch Type</b>	Decorator Paddle Push with Indicator
<b>Z-Wave Scene Type</b>	Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 1000W Dimmer

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x3301
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.61.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

### Association Group Information

**Group # / Max**    **Description**

#### Nodes

1 / 5            • Z-Wave Plus™ Lifeline: A NOTIFICATION frame is sent to the nodes in this association group when a Lifeline event occurs. • All nodes in the association group

#### Supported Command Classes (14):

Association Group Information V3	Association V2
Basic V2	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Switch All	Switch Multilevel V4
Version V2	Z-Wave Plus Info V2

#### Controlled Command Classes (1):

Hail