

Z-Wave Protocol Implementation Conformance Statement

Siren Alarm

General Information

Product Identifier:	NAS-AB01Z
Brand Name:	Coolcam
Product Version:	HW: 48 FW: 2.65
Z-Wave Certification #:	ZC10-16105297

Product Features

Battery Type	CR123A
Color	White
Communications Connections	RS-232 (Serial)
Communications Protocol	Z-Wave Serial API
Firmware Updatable	Updatable by Manufacturer
Z-Wave Scene Type	Scene
Battery Quantity	2

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Siren Alarm

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0088
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.08
Z-Wave Library Type:	Routing Slave
Z-Wave Device Type / Role Type:	Siren / Listening Sleeping Slave

Association Group Information

Group # / Max	Description
----------------------	--------------------

Nodes

1 / 5	GROUP 1 is lifeline service that assigned to Siren status. It enables the Siren to send reports and readings to Z Wave Controller or Z Wave Gateway whenever the sensor is triggered. This Group Support: SWITCH_BINARY_REPORT, NOTIFICATION_REPORT, BATTERY_REPORT, DEVICE_RESET_LOCALLY_NOTIFICATION
2 / 5	GROUP 2 allows for Send Binary Switch Report to associated devices in this group. This Group Support: SWITCH_BINARY_REPORT
3 / 5	GROUP 3 allows for Send Notification to associated devices in this group. This Group Support: NOTIFICATION_REPORT