

Z-Wave Protocol Implementation Conformance Statement

nexTouch Wireless Push Button with Z-Wave

General Information

| | |
|--------------------------------|------------------------|
| Product Identifier: | NTB610-ZW2 |
| Brand Name: | Yale Locks & Hardware |
| Product Version: | HW: 255 FW: 1.67:15.00 |
| Z-Wave Certification #: | ZC10-16095224 |

Product Features

| | |
|--------------------------------------|-----------------------------|
| Battery Quantity | 4 |
| Battery Type | AA |
| Color | Chrome |
| Door Lock Type | Lever Handle |
| Firmware Updatable | Updatable by Consumer by RF |
| IP (Ingress Protection) Rated | Yes |
| Outdoor Use | Yes |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

nexTouch Wireless Push Button with Z-Wave

Z-Wave Technical Information

| | |
|--|---|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x0B00 |
| Z-Wave Product Type: | 0x8001 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.51.07 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Door Lock - Keypad / Listening Sleeping Slave |

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (18):

| | |
|--------------------------|------------------------------|
| Association Group Info | Association V2 |
| Battery | Configuration |
| Device Reset Locally | Door Lock Logging |
| Door Lock V2 | Firmware Update Meta-Data V3 |
| Manufacturer Specific V2 | Notification V4 |
| Powerlevel | Schedule Entry Lock V3 |
| Security S0 | Time Parameters |
| Time V2 | User Code |
| Version V2 | Z-Wave Plus Info V2 |