

## Z-Wave Protocol Implementation Conformance Statement

# DCH-Z122 mydlink™ Motion Sensor

### General Information

<b>Product Identifier:</b>	DCH-Z122
<b>Brand Name:</b>	D-Link Corporation
<b>Product Version:</b>	HW: 1 FW: 1.27:01.21
<b>Z-Wave Certification #:</b>	ZC10-16115304

### Product Features

<b>Battery Quantity</b>	1
<b>Battery Type</b>	CR123A
<b>Color</b>	White
<b>Sensors</b>	Motion/No Motion (Binary)

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0035
<b>Z-Wave Product Type:</b>	0x0002
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## DCH-Z122 mydlink™ Motion Sensor

2 / 8

light control

### Supported Command Classes (14):

Association Group Info

Battery

Device Reset Locally

Multi-Command

Powerlevel

Sensor Binary V2

Wake Up V2

Association V2

Configuration

Manufacturer Specific V2

Notification V4

Security S0

Version V2

Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic