

## Z-Wave Protocol Implementation Conformance Statement

# DCH-Z112 mydlink™ Door/Window Sensor

### General Information

<b>Product Identifier:</b>	DCH-Z112
<b>Brand Name:</b>	D-Link Corporation
<b>Product Version:</b>	HW: 1 FW: 1.01
<b>Z-Wave Certification #:</b>	ZC10-16115303

### Product Features

<b>Battery Type</b>	CR123A
<b>Sensors</b>	Open/Closed (Binary)
<b>Battery Quantity</b>	1

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0034
<b>Z-Wave Product Type:</b>	0x0002
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.61.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

### Association Group Information

Group # / Max	Description
Nodes	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## DCH-Z112 mydlink™ Door/Window Sensor

### Supported Command Classes (11):

Association Group Info  
Battery  
Manufacturer Specific V2  
Powerlevel  
Version V2  
Z-Wave Plus Info V2

Association V2  
Device Reset Locally  
Notification V4  
Security S0  
Wake Up V2